

Service: Cleaning instructions



Service: Cleaning instructions

You have opted for professional operating controls that are “Made in Germany” now that you have purchased a data input device made by GETT Gerätetechnik GmbH. We would like to support you with recommendations on how to clean the units and suitable cleaning agents so that the design and functions are maintained for as long as possible.

If you are uncertain about using your preferred cleaning agent or disinfectant, you can contact us at any time.

Cleaning stainless steel

Use a soft cloth and normal cleaning agents suitable for stainless steel surfaces when cleaning our keyboards. Place a small amount of the cleaner on the dampened cloth and remove any dirt with circular movements and only slight pressure. Then wipe the cleaned surface with a damp cloth in order to remove any remaining cleaning agent. When disinfecting, we recommend that you use an alcohol-based disinfectant in line with the manufacturer’s specifications.

Never use any abrasive substances, such as steel wool or aggressive scouring agents, to remove stubborn marks. Do not use any cleaning agents containing substances that are listed as *non-resistant* in the following table.

Resistance [stainless steel](#)

Cleaning glass, silicone and film

Use a soft cloth and a vinegar-based household cleaner to clean our keyboards. Exert slight pressure with the cloth, which has been soaked with the cleaner and then squeezed out, and remove any dirt with circular movements. Then wipe the cleaned surface with a damp cloth in order to remove any remaining cleaning agent. When disinfecting, we recommend that you use an alcohol-based disinfectant in line with the manufacturer’s specifications.

Never use any abrasive substances, such as steel wool or aggressive scouring agents, to remove stubborn marks. Do not use any cleaning agents containing substances that are listed as *non-resistant* in the following table.

Resistance [glass](#), [silicone](#) and [film](#)